


# BOGGLE™ SHORT SPECIFICATION SHEET



Fixture Type	Fixture Code	Quantities

# 1 HOW TO ORDER

## 1. LUMINAIRE

**BGGC1C** Direct

One power cord for every 50 linear feet.

## 2. LENGTH OF RUN

The minimum order length is 4ft, with lengths available in 2ft increments.

SFA\_\_\_\_

The minimum order length is 4ft, with lengths available in 2ft increments.

### 3. LENGTH

**SL02** 2ft 1 **SL04** 4ft **SL06** 6ft **SL08** 8ft

**SL10** 10ft **SL12** 12ft

# 4. BAFFLE

BL1 White Baffle (Gloss) BL2 Black Baffle (Gloss) BL3 White Baffle (Matte) BL4 Black Baffle (Matte)

Data shown based on max values. Consult Performance Data download for more details.

<sup>&</sup>lt;sup>1</sup> Consult factory if a 2ft length is required.



**LPF020** 200 lm/ft **LPF040** 400 lm/ft **LPF060** 600 lm/ft **LPF080** 800 lm/ft

**LPF100** 1000 lm/ft

6. CRI

CR90 CRI 90+

**7. CCT** 

**CTA27** 2700K **CTA30** 3000K **CTA35** 3500K **CTA40** 4000K

CTA60 Tunable White 1

## 8. VOLTAGE

**V1** 120/277V **V2** 240V <sup>1</sup> **V3** 347V <sup>2</sup> **V4** Low Voltage <sup>3</sup>

## 9. DIMMING

**DA01** 0-10V Dimming 1.0% **DA02** 0-10V Dimming 0.1% <sup>1</sup> **DA20** DALI Dimming 0.1% <sup>1</sup> **DA21** DALI Dimming 1.0% <sup>1</sup>

DA30 DSI/switchDim <sup>2</sup> DA45 PoE <sup>3</sup>

#### 10. FINISH

FA01 White - Textured FA02 Black Metallic - Textured FA20 Silver Metallic - Textured FA27 Wood grain - Light Cherry <sup>1</sup>

FA28 Wood grain - Dark Walnut 1

<sup>&</sup>lt;sup>1</sup> Tunable White is available with 0-10V dimming options only. Consult factory for details.

<sup>&</sup>lt;sup>1</sup> Not available in North America.

<sup>&</sup>lt;sup>2</sup> Only available with DA01 dimming.

<sup>&</sup>lt;sup>3</sup> Only available with DA45 dimming.

<sup>&</sup>lt;sup>1</sup> Not available with V3. DALI dimming (DA20 & DA21) not available with CTA60 (Tunable white).

<sup>&</sup>lt;sup>2</sup> Not available in North America. Not available with CTA60 (Tunable white).

<sup>&</sup>lt;sup>3</sup> Only available with V4.

<sup>&</sup>lt;sup>1</sup> Longer than normal lead times, consult factory.



### 11. EMERGENCY

E0 Not required E1 Emergency system - Integral <sup>1</sup> E3 Emergency generated circuit - Remote <sup>1</sup>

<sup>&</sup>lt;sup>1</sup> A drawing will be required at time of ordering to determine the required number and location of the emergency sections or generator circuits. Not available in 347V. Available upon request, consult factory for details.