

1 PERFORMANCE DATA

| 2FT DIRECT | Lumens | WATTS | LPW | 2FT INDIRECT | Lumens | WATTS | LPW |
|------------|--------|-------|-----|--------------|--------|-------|-----|
| LMA0230 | 2300 | 25 | 91 | LMB0110 | 1100 | 9 | 123 |
| LMA0460 | 4600 | 50 | 91 | LMB0220 | 2200 | 18 | 123 |

| 3FT DIRECT | Lumens | WATTS | LPW | 3FT INDIRECT | Lumens | WATTS | LPW |
|------------|--------|-------|-----|--------------|--------|-------|-----|
| LMA0230 | 2300 | 25 | 92 | LMB0110 | 1100 | 9 | 123 |
| LMA0460 | 4600 | 50 | 92 | LMB0220 | 2200 | 18 | 123 |
| LMA0670 | 6700 | 73 | 92 | LMB0440 | 4400 | 36 | 123 |

| 4FT DIRECT | Lumens | WATTS | LPW | 4FT INDIRECT | Lumens | WATTS | LPW |
|------------|--------|-------|-----|--------------|--------|-------|-----|
| LMA0460 | 4600 | 50 | 92 | LMB0110 | 1100 | 9 | 123 |
| LMA0670 | 6700 | 73 | 92 | LMB0220 | 2200 | 18 | 123 |
| LMA0880 | 8800 | 96 | 91 | LMB0440 | 4400 | 36 | 123 |

| 5FT DIRECT Direct | Lumens | WATTS | LPW | 5FT INDIRECT | Lumens | WATTS | LPW |
|-------------------|--------|-------|-----|--------------|--------|-------|-----|
| LMA0670 | 6700 | 73 | 91 | LMB0220 | 2200 | 18 | 123 |
| LMA0880 | 8700 | 96 | 91 | LMB0440 | 4400 | 36 | 123 |
| LMA1100 | 11000 | 120 | 91 | LMB0730 | 7300 | 59 | 123 |

| 6FT DIRECT Direct | Lumens | WATTS | LPW | 6FT INDIRECT | Lumens | WATTS | LPW |
|-------------------|--------|-------|-----|--------------|--------|-------|-----|
| LMA0880 | 8800 | 96 | 92 | LMB0440 | 4400 | 36 | 123 |
| LMA1100 | 11000 | 120 | 92 | LMB0730 | 7300 | 59 | 123 |
| LMA1300 | 13000 | 142 | 92 | LMB0880 | 8800 | 71 | 123 |

| 7FT DIRECT Direct | Lumens | WATTS | LPW | 7FT INDIRECT | Lumens | WATTS | LPW |
|-------------------|--------|-------|-----|--------------|--------|-------|-----|
| LMA1100 | 11100 | 122 | 91 | LMB0730 | 7300 | 59 | 123 |
| LMA1300 | 13100 | 144 | 91 | LMB0880 | 8800 | 71 | 123 |
| LMA1500 | 15200 | 167 | 91 | LMB1200 | 11700 | 95 | 123 |

| 8FT DIRECT Direct | Lumens | WATTS | LPW | 8FT INDIRECT | Lumens | WATTS | LPW |
|-------------------|--------|-------|-----|--------------|--------|-------|-----|
| LMA1300 | 13300 | 171 | 78 | LMB0440 | 4400 | 36 | 123 |
| LMA1500 | 15300 | 197 | 78 | LMB0730 | 7300 | 59 | 123 |
| LMA2100 | 21500 | 277 | 78 | LMB0880 | 8800 | 71 | 123 |

| 9FT DIRECT | | | | 9FT INDIRECT | | | |
|------------|--------|-------|-----|--------------|--------|-------|-----|
| | Lumens | WATTS | LPW | | Lumens | WATTS | LPW |
| LMA1500 | 15100 | 191 | 79 | LMB0880 | 8800 | 71 | 123 |
| LMA2100 | 21100 | 268 | 79 | LMB1200 | 12000 | 97 | 123 |
| LMA2400 | 24100 | 307 | 79 | LMB1300 | 13100 | 107 | 123 |

| 12FT DIRECT | | | | 12FT INDIRECT | | | |
|-------------|--------|-------|-----|---------------|--------|-------|-----|
| | Lumens | WATTS | LPW | | Lumens | WATTS | LPW |
| LMA2100 | 21200 | 269 | 79 | LMB1200 | 12000 | 97 | 123 |
| LMA2400 | 24200 | 307 | 79 | LMB1300 | 13100 | 107 | 123 |
| LMA3200 | 32300 | 410 | 79 | LMB1800 | 17500 | 142 | 123 |

| 18FT DIRECT | | | | 18FT INDIRECT | | | |
|-------------|--------|-------|-----|---------------|--------|-------|-----|
| | Lumens | WATTS | LPW | | Lumens | WATTS | LPW |
| LMA2400 | 24200 | 307 | 79 | LMB1300 | 13100 | 107 | 123 |
| LMA3200 | 32200 | 410 | 79 | LMB1800 | 17500 | 142 | 123 |
| LMA4800 | 48400 | 615 | 79 | LMB3100 | 30700 | 249 | 123 |