

# WARP™ - POWER CORD SUSPENDED



Project Name:

Fixture Type:

Fixture Code:

Quantities:

## A. LUMINAIRE

**WARP1P18** 18", Direct, 3300 lms Direct    **WARP1P24** 24", Direct, 4900 lms Direct    **WARP2P18** 18", Direct/Indirect, 3300 lms Direct, 2400 lms Indirect    **WARP2P24** 24", Direct/Indirect, 4900 lms Direct, 2400 lms Indirect

## B. LUMENS (DIRECT)

**LMA0200** 2000 lm    **LMA0330** 3300 lm    **LMA0490** 4900 lm

## C. LUMENS (INDIRECT)

**LMB0000** Not required    **LMB0120** 1200 lm    **LMB0180** 1800 lm    **LMB0240** 2400 lm

## D. CRI

**CR80** CRI 80+

## E. CCT

**CTA30** 3000K    **CTA35** 3500K    **CTA40** 4000K

## F. UPLIGHT DIFFUSER

**UD0** Not required    **UD1** Clear diffuser    **UD2** Opal diffuser

## G. VOLTAGE

**V1** 120/277V    **V2** 240V<sup>1</sup>    **V3** 347V<sup>2</sup>

<sup>1</sup> Not available in North America.

<sup>2</sup> Available with DA01 dimming only.

## H. DIMMING

**DA01** 0-10V Dimming 1.0%    **DA02** 0-10V Dimming 0.1%<sup>1</sup>    **DA20** DALI Dimming 0.1%<sup>1</sup>    **DA21** DALI Dimming 1.0%<sup>1</sup>  
**DA30** DSI/switchDim<sup>1 2</sup>

<sup>1</sup> Not available with V3.

<sup>2</sup> Not available in North America.

## I. FIXTURE FINISH

**FA01** White    **FA02** Black Metallic - Textured    **FA20** Silver Metallic - Textured    **FA25** Gold Metallic  
**FA44** Midnight Blue Metallic - Textured    **FA45** Copper Metallic    **FA46** Charcoal Metallic - Textured    **FA47** Bronze Metallic - Textured  
**FA52** Champagne Metallic    **FA53** Red Metallic - Textured

## J. CANOPY FINISH

**CF01** White    **CF02** Black Metallic - Textured    **CF20** Silver Metallic - Textured    **CF25** Gold Metallic  
**CF44** Midnight Blue Metallic - Textured    **CF45** Copper Metallic    **CF46** Charcoal Metallic - Textured    **CF47** Bronze Metallic - Textured  
**CF52** Champagne Metallic    **CF53** Red Metallic - Textured

## K. EMERGENCY

**E0** Not required    **E1** Emergency system - Integral    **E2** Emergency system - Remote



# WARP™ - POWER CORD SUSPENDED

## L. DOWNLIGHT SPOT

**DL00** Not required

**DL27** Downlight 28W, 2700K (1730 delivered lms)

**DL30** Downlight 28W, 3000K (1799 delivered lms)

**DL35** Downlight 28W, 3500K (1854 delivered lms)

**DL40** Downlight 28W, 4000K (1858 delivered lms)

## CIRCUITS

**CS1** Single Circuit <sup>1</sup>

**CS2** Dual Circuit <sup>2</sup>

**CS3** Triple Circuit <sup>3</sup>

<sup>1</sup> The entire fixture will be on one circuit, 1 power cable will be supplied.

<sup>2</sup> Spot light will be on a separate circuit from the main fixture. One power cable will be supplied. If the Spot light is not selected, then Direct and Indirect will be on a separate circuit.

<sup>3</sup> Direct, Indirect and Spot light will all be on separate circuits. Two power cables will be supplied.



# WARP™ - POWER CORD SUSPENDED

## DIMENSIONAL DIAGRAMS

