

# MACRO QUAD™ - SUSPENDED



Project Name:	Fixture Type:
Fixture Code:	Quantities:

## A. LUMINAIRE

<b>MCQP1P02</b> 2ft SQ Direct, 8500 lms	<b>MCQP1P03</b> 3ft SQ Direct, 12800lms	<b>MCQP1P04</b> 4ft SQ Direct, 17000lms	<b>MCQP1P05</b> 5ft SQ Direct, 21300lms
<b>MCQP1P06</b> 6ft SQ Direct, 25500lms	<b>MCQP1P07</b> 2ft x 4ft Direct, 12800 lms	<b>MCQP1P08</b> 3ft x 6ft Direct, 19100 lms	<b>MCQP2P02</b> 2ft SQ Direct/Indirect. 12300lms
<b>MCQP2P03</b> 3ft SQ Direct/Indirect, 18500 lms	<b>MCQP2P04</b> 4ft SQ Direct/Indirect, 24600 lms	<b>MCQP2P05</b> 5ft SQ Direct/Indirect, 30800 lms	<b>MCQP2P06</b> 6ft SQ Direct/Indirect, 36900 lms
<b>MCQP2P07</b> 2ft x 4ft Direct/Indirect, 18500lms	<b>MCQP2P08</b> 3ft x 6ft Direct/Indirect, 27700lms		

Consult factory for other sizes.

## B. LMS/FT (DIRECT)

<b>LPF057</b> 575 lm/ft <sup>1</sup>	<b>LPF085</b> 850 lm/ft <sup>2</sup>	<b>LPF115</b> 1150 lm/ft <sup>3</sup>
--------------------------------------	--------------------------------------	---------------------------------------

<sup>1</sup> Based of 50% of total output.  
<sup>2</sup> Based on 75% of total output.  
<sup>3</sup> 100% of total output.

## C. LUMENS/FT (INDIRECT)

<b>LPG000</b> Not required	<b>LPG025</b> 250 lm/ft <sup>1</sup>	<b>LPG037</b> 375 lm/ft <sup>2</sup>	<b>LPG050</b> 500 lm/ft <sup>3</sup>
----------------------------	--------------------------------------	--------------------------------------	--------------------------------------

<sup>1</sup> Based of 50% of total output.  
<sup>2</sup> Based on 75% of total output.  
<sup>3</sup> 100% of total output.

## D. CRI

**CR80** CRI 80+

## E. CCT (DIRECT)

<b>CTA30</b> 3000K	<b>CTA35</b> 3500K	<b>CTA40</b> 4000K
--------------------	--------------------	--------------------

## F. CCT (INDIRECT)

<b>CTB00</b> Not required	<b>CTB30</b> 3000K	<b>CTB35</b> 3500K	<b>CTB40</b> 4000K
---------------------------	--------------------	--------------------	--------------------

## G. UPLIGHT DIFFUSER

<b>UD0</b> Not required	<b>UD1</b> Clear diffuser	<b>UD2</b> Opal diffuser <sup>1</sup>
-------------------------	---------------------------	---------------------------------------

<sup>1</sup> 10% reduction on indirect lumens.

## H. VOLTAGE

<b>V1</b> 120/277V	<b>V2</b> 240V <sup>1</sup>	<b>V3</b> 347V <sup>2</sup>	<b>V4</b> Low Voltage <sup>3</sup>
--------------------	-----------------------------	-----------------------------	------------------------------------

<sup>1</sup> Not available in North America.  
<sup>2</sup> Available with DA01 dimming only.  
<sup>3</sup> Only available with DA45 dimming.

# MACRO QUAD™ - SUSPENDED

## I. DIMMING

<b>DA01</b> 0-10V Dimming 1.0%	<b>DA02</b> 0-10V Dimming 0.1% <sup>1</sup>	<b>DA20</b> DALI Dimming 0.1% <sup>1</sup>	<b>DA21</b> DALI Dimming 1.0% <sup>1</sup>
<b>DA30</b> DSI/switchDim <sup>2</sup>	<b>DA45</b> PoE <sup>3</sup>		

<sup>1</sup> Not available with V3.  
<sup>2</sup> Not available in North America.  
<sup>3</sup> Only available with V4.

## J. FIXTURE FINISH

<b>FA01</b> White	<b>FA02</b> Black Metallic - Textured	<b>FA20</b> Silver Metallic - Textured	<b>FA25</b> Gold Metallic - Textured
<b>FA27</b> Wood grain - Light Cherry <sup>1</sup>	<b>FA28</b> Wood grain - Dark Walnut <sup>1</sup>	<b>FA44</b> Midnight Blue Metallic - Textured	<b>FA45</b> Copper Metallic
<b>FA46</b> Charcoal Metallic - Textured	<b>FA47</b> Bronze Metallic - Textured	<b>FA52</b> Champagne Metallic	<b>FA53</b> Red Metallic - Textured

<sup>1</sup> Longer lead time may apply, consult factory.

## K. CANOPY FINISH

<b>CF01</b> White	<b>CF02</b> Black Metallic - Textured	<b>CF20</b> Silver Metallic - Textured	<b>CF25</b> Gold Metallic - Textured
<b>CF44</b> Midnight Blue Metallic - Textured	<b>CF45</b> Copper Metallic	<b>CF46</b> Charcoal Metallic - Textured	<b>CF47</b> Bronze Metallic - Textured
<b>CF52</b> Champagne Metallic	<b>CF53</b> Red Metallic - Textured		

## L. ACOUSTIC PANEL FINISH

<b>AP00</b> Not required	<b>AP04</b> White	<b>AP13</b> Apple Green	<b>AP22</b> Blue
<b>AP11</b> Light Gray	<b>AP26</b> Sesame Gray	<b>AP27</b> Black	

Consult website to view available panel finishes.

## M. EMERGENCY

<b>E0</b> Not required	<b>E1</b> Emergency system - Integral <sup>1</sup>	<b>E2</b> Emergency system - Remote <sup>2</sup>
------------------------	--	--

<sup>1</sup> Direct illumination only, not available with 347V.

## N. CIRCUITS

<b>CS1</b> Single circuit	<b>CS2</b> Dual circuit <sup>1</sup>
---------------------------	--------------------------------------

<sup>1</sup> Supplied with two power cables

## O. CONTROLS

<b>C0</b> Not required	<b>C1</b> Encelium/Zigbee
------------------------	---------------------------

# MACRO QUAD™ - SUSPENDED

## DIMENSIONAL DIAGRAMS



MACRO QUAD™ - SUSPENDED

